



385 Kimbark Street, Longmont, CO 80501
T 303-651-8332 F 303-651-8930
building.inspection@longmontcolorado.gov

DO NOT HESITATE TO ASK YOUR INSPECTOR QUESTIONS

This guideline has been prepared to assist the lay person in complying with the requirements of all Longmont adopted Electrical Codes, and assure the installation of a safe and reliable electrical system. This guideline is not inclusive for every installation and is not an instruction manual.

Along with meeting NEC requirements, the permit and inspection process defined by ordinance must be followed.

Check our web site (http://www.ci.longmont.co.us/bldginsp/adopted/index.htm) for the currently adopted codes and the City's local adopted amendments. In addition, check with Longmont Power and Communications (303-651-8386) for their requirements.

1. ELECTRIC SERVICE

The service equipment must be large enough to supply the connected load, which is calculated using Article 220 of the NEC. The most common sizes of residential service equipment are 100, 125, 150, and 200 amperes. The minimum wire size for service entrance conductors per 310.15 (b)6 are listed below:

Conductor Types and Sizes for 120/240-Volt, 3-Wire, Single-Phase Dwelling Services

RH, RHH, RHW, RHW-2, THHN, THHW, THW, THWN, XHHW, USE*

*Type "USE" (Underground Service Entrance) conductors are not permitted to enter a building.

Table with 3 columns: COPPER, ALUMINUM AND COPPER CLAD ALUMINUM, SERVICE RATING IN AMPS. Rows show AWG sizes from 4 to 2/0 and corresponding service ratings from 100 to 200.

The service equipment must be grounded in accordance with Article 250 of the NEC, which, in general, says the neutral must be bonded to the grounding electrode system at the main service enclosure.

The main service disconnect shall be mounted either outside or inside the dwelling. The main is allowed inside only when the panel and meter enclosure are mounted directly back to back. All service equipment and electrical panels shall have a clear area 6'6" high, 30" wide and 36" deep in front. This clear area must extend from floor to 6'6" high with no intrusions from other equipment, cabinets, counters, appliances, etc. Panels are NOT permitted in clothes closets or bathrooms.

In the main service equipment, the neutral and equipment grounding conductors are bonded together; in sub-panels, the neutral is isolated from the grounding conductor. A concrete encased electrode is required on all new buildings. The electric meter enclosure should be mounted at 5' 6" above finish grade, at the center of the meter opening. Overhead drops should have a clearance of 10' above finish grade to the bottom of the drip loop.



385 Kimbark Street, Longmont, CO 80501
T 303-651-8332 F 303-651-8930
building.inspection@longmontcolorado.gov

2. BRANCH CIRCUIT WIRING

Type NM (Romex) sized #12/2 w/ground and #14/2 w/ground are used for lighting and general purpose receptacle circuits. #10/2 w/ground is commonly used for electric water heaters, #10/3 w/ground for electric dryers, and #8/3 cu w/ground & #6/3 cu w/ground for ranges and wall mounted ovens.

The cables must be protected by over-current devices (circuit breakers), which do not exceed their rated ampacity. The rated ampacities for cable types are listed below:

Table with 2 columns: COPPER NM CABLE and TYPE S.E., AND S.E.R. ALUMINUM CABLE. Rows list ampere ratings for various wire sizes like #14, #12, #10, #8 cu, #6 cu.

It is important to note that if for example you begin a circuit with #12, you must use this same wire size throughout. You should not mix different wire sizes on the same branch circuit.

Type NM cable must be stapled within 12" of metal boxes, 8" of plastic boxes and every 4 1/2 feet thereafter. Proper connectors must be used where NM cable enters metal cabinets, boxes or panel boards.

When Type NM cable is installed parallel to framing members, or in bored holes, it shall be located at least 1 1/4" from the nearest edge of the framing member, where nails or screws may penetrate the cables. If this distance cannot be maintained, the cable shall be protected by a steel plate or sleeve at least 1/16" thick. Article 300-4(d).

Cable or raceway-type wiring methods installed in a groove, to be covered by paneling, carpeting, or similar finish, shall be protected by a 1/16-inch steel plate, sleeve, or equivalent, or must be recessed in the groove 1 1/4-inch for the full length of the groove in which the cable or raceway is installed.

Ceiling mounted paddle fans shall be supported by outlet boxes identified for such use. NEC 314.27d

3. REQUIRED BRANCH CIRCUITS for Dwellings

- a. Small Appliance Branch Circuits - The NEC requires a minimum of two 20 ampere branch circuits to feed receptacle outlets for small appliance loads...
b. Laundry Branch Circuit - One 20 amp branch circuit must be provided for the laundry.
c. Bathroom Receptacles - At least one 20 amp circuit for bathroom receptacle outlets shall be supplied.
d. Central Heat / AC - Central heating equipment shall be supplied by an individual branch circuit...
e. General Lighting Branch Circuits - Shall be computed on a three watts per square foot basis.

4. REQUIRED RECEPTACLE OUTLETS (Tamper resistant required below 48 inches.)

- a. At least one outlet shall be installed in bathrooms within 36 inches of the outside edge of each basin. The receptacle outlet shall be located on a wall that is adjacent to the basin location.



385 Kimbark Street, Longmont, CO 80501
T 303-651-8332 F 303-651-8930
building.inspection@longmontcolorado.gov

- b. At least one gfi protected outlet shall be installed in every attached garage, and one gfi outlet in every detached garage with electric power.
- c. At least two gfi protected outlets shall be installed outdoors, one on the front and one on the back of the dwelling, accessible at grade level.
- d. At least one gfi protected receptacle must be installed in the unfinished portion of the basement. This receptacle is in addition to any receptacles that may be installed for laundry or other specific purposes.
- e. In every kitchen, family room, dining room, living room, parlor, library, den, sun room, bedroom, recreation room or similar room, or area of dwelling units, receptacle outlets shall be installed so that no point along the floor line in any wall space is more than six feet horizontally, measured from an outlet in that space, including any wall space two feet or more in width, and excluding only that space occupied by sliding panels in exterior walls. The wall space afforded by fixed room dividers, such as freestanding bar-type counters or railings, shall be included in the six foot measurement. A receptacle outlet is required in any dwelling unit hallway that is ten feet or more in length. No outlets may be installed over an electric baseboard heater.
- f. In kitchens and dining areas, a gfi protected receptacle outlet shall be installed at each counter space wider than 12". Countertop receptacles shall be installed so that no point along the wall line is more than 24" measured horizontally from a receptacle outlet in that space. Peninsular bars and islands 12" or wider shall have at least one receptacle within 12 inches of countertop surface and with less than a 6 inch countertop overhang.
- g. Receptacles installed in the floor must use a box-receptacle combination designed specifically for that purpose. Receptacles installed in the floor within 18" of the wall may be used in place of wall mounted receptacles.
- h. At least one 15 or 20 ampere, 125 volt GFCI protected receptacle must be installed at an indoor spa or hot tub location, not closer than five feet from the inside wall of the unit and not more than ten feet away from it. Light fixtures, outlets and ceiling fans over spas and hot tubs shall be a minimum of 7'6" above the maximum water level. Outdoors spa or hot tubs have the same requirements as a swimming pool. Check with your inspector for those requirements.
- i. Dwelling Units. All 120-volt, single phase, 15- and 20-ampere branch circuits supplying outlets installed in dwelling unit family rooms, dining rooms, living rooms, parlors, libraries, dens, bedrooms, sunrooms, recreation rooms, closets, hallways, or similar rooms or areas shall be protected by a listed arc-fault circuit interrupter, combination-type, installed to provide protection of the branch circuit.

NOTE:
Arc-Fault Circuit-Interrupter Protection: an arc-fault circuit interrupter is a device intended to provide protection from the effects of arc faults by recognizing characteristics unique to arcing and by functioning to de-energize the circuit when an arc fault is detected.

5. REQUIRED LIGHTING OUTLETS

- a. At least one wall switch-controlled lighting outlet shall be installed in every habitable room; in bathrooms, hallways, stairways, attached garages, detached garages with electric power, and at outdoor entrances or exits. The lighting outlet for interior stairways shall have a wall switch at each floor level where the difference between floor levels is six steps or more.
- b. At least one wall switch controlled lighting outlet shall be installed in an attic, under-floor space, utility room, and basement, where these spaces are used for storage or contain equipment requiring servicing. The switch shall be located at the point of entry to these areas, and the lighting outlet located at or near the equipment requiring servicing.

Identification of switch leg:



385 Kimbark Street, Longmont, CO 80501
T 303-651-8332 F 303-651-8930
building.inspection@longmontcolorado.gov

Circuits of 50 Volts or More. The use of insulation that is white or natural gray or that has three continuous white stripes for other than a grounded conductor for circuits of 50 volts or more shall be permitted if part of a cable assembly and where the insulation is permanently re-identified to indicate its use as an ungrounded conductor, by painting or other effective means at its termination, and at each location where the conductor is visible and accessible.

6. GROUND FAULT PROTECTION

All receptacles listed below must be protected by a ground fault circuit interrupter:

- a. Bathrooms receptacles.
- b. All outdoor receptacles.
- c. Garage receptacles except those not readily accessible such as ceiling mounted receptacles.
- d. Kitchen receptacles that serve counter top surfaces.
- e. Receptacles within 6 feet of a wet bar sink.
- f. All receptacles in an unfinished basement or crawl space at or below grade.
- g. Single receptacle within a dedicated location and identified for specific use by a cord and plug connected appliance.
- h. Single receptacle serving a permanently installed sump pump.
- i. Hydro-massage bath tubs.
- j. Spas and Hot tubs, water features and associated electrical components.

7. REQUIRED DISCONNECTING MEANS

Disconnects are required within sight of all hardwired equipment. See 422.30 for any exceptions.

8. CONDUCTOR FILL

Outlet and junction boxes shall be of sufficient size to provide free space for all conductors and devices enclosed in the box. All outlet boxes have a specific volume, measured in cubic inches. For example, if you have two #12/2, with ground NM-B cables entering a box with one duplex receptacle, you would need a box with a minimum volume of 15.75 cubic inches. Each #12 that enters the box needs 2.25 cubic inches with the exception of the grounding conductor which requires one 2.25 cubic inch for all of the grounds. Also, each strap containing one or more devices is counted as the equivalent of two conductors; therefore, $2.25 \times 7 = 15.75$.

VOLUME REQUIRED PER CONDUCTOR:

- #6 - 5 cubic inches
- #8 - 3 cubic inches
- #10 - 2.5 cubic inches
- #12 - 2.25 cubic inches
- #14 - 2 cubic inches

9. EQUIPMENT GROUNDING CONDUCTOR MAKE-UP

All equipment grounding conductors must be connected together with solder-less pressure connectors such as green wire-nuts or crimp sleeves, leaving sufficient extra conductor (minimum 6 inches free before the splice) for attachment to the metal box and/or device. When crimp type connectors are used, they must be crimped using the tool recommended by the manufacturer.

Please note that all metal junction and outlet boxes must be grounded by attaching the equipment grounding conductor out of the NM cable to the metal box using an approved screw or grounding clip. When circuit conductors are



385 Kimbark Street, Longmont, CO 80501
T 303-651-8332 F 303-651-8930
building.inspection@longmontcolorado.gov

made up, six inches of free conductor measured from the back of the box, must be left for use in make-up and for the attachment of devices.

10. ELECTRIC HEAT CIRCUITRY

Electric heat may be installed on 15, 20, or 30 amp branch circuits. Listed below is the maximum wattage that may be installed on each size branch circuit. (All circuits are figured at 240 v)

- 15A - 2,880 watts maximum
- 20A - 3,840 watts maximum
- 30A - 5,760 watts maximum

For example, if you are installing baseboard heaters which are typically rated at approximately 250 watts a linear foot, you could potentially install 12 feet maximum length on a 20 amp, 230 volt circuit at continuous duty use meaning the branch circuit must be capable of handling 125% of the load.

11. ROUGH-IN INSPECTION

At the time you call for rough-in inspection, you should have all wire pulled, secured properly, and all splices made up and ready to accept devices and fixtures. Please DO NOT install any devices or cover any wiring with insulation or wall coverings, i.e., drywall or paneling. Requirements of # 9 above must be completed prior to the rough inspection.

The building code requires interconnected hard wired battery backup smoke detectors, one on each level, one in the hallway or area serving a sleeping room and one in each sleeping room. Additionally in areas where the ceiling height changes 24" or more on the same level another smoke detector must be installed in the upper ceiling level. Check the manufacture's installation instructions for smoke detectors placement. For all remodel projects, check with the inspector for smoke and carbon monoxide detector requirements.

12. FINAL INSPECTION

The electrical installation should be complete at the time of request. All devices, fixtures and equipment shall be complete, and the panel labeled properly. All wiring shall be free from short circuits, ground faults and open circuits. The space should be ready to occupy meaning all flooring etc. should be complete.

DO NOT HESITATE TO ASK YOUR INSPECTOR QUESTIONS